



UniFi UISP Branding

Search UniFi products

Switching WiFi Physical Security Door Access Integrations Advanced Hosting

Network Storage > UNAS Pro 8






UNAS Pro 8

UNAS-Pro-8

Datasheet

- In The Box
- Marketing Images
- Accessories
- Installation Guide



Overview

Dimensions	442.4 x 480 x 87.4 mm (17.4 x 18.9 x 3.4")
Storage Capacity	(8) 2.5/3.5" drive bays (2) M.2 NVMe bays
Networking Interface	(2) 10G SFP+ (10G Only) (1) 10 GbE RJ45 (10G/5G/2.5G/1G/100M)
Power Redundancy	✓ ⓘ
Form Factor	Rack mount (2U)

Hardware


Hard Drive Capacity	(8) 2.5/3.5" HDD / SSD support (2) M.2 NVMe SSD support
Max. Power Budget for Drives	225W

Max. Power Consumption	250W
Power Method	(2) AC input, Hot-swappable power modules
Power Supply	(2) Hot-swappable AC/DC 550W power modules
Processor	Quad-Core ARM® Cortex®-A57 at 2.0 GHz
Memory	16 GB
Management	Ethernet
RF Interface	Bluetooth 4.1
Weight	11.5 kg (25.35 lb)
Enclosure Material	SGCC steel
Mount Material	SGCC steel
Supported Rack Depth	The rails support 600 mm (23.6") four-post racks with square holes (9.5 x 9.5 mm) Posts depths ranging from 600-1066 mm (23.6-42")
LEDs	
Ethernet	✓
SFP+	✓
HDD	✓
System	✓
Ambient Operating Temperature	-5 to 40° C (23 to 104° F)
Ambient Operating Humidity	5 to 95% noncondensing
NDAA Compliant	✓
Certifications	FCC, CE, IC, SRRC
^ Software	
Supported File Protocols	
NFS	✓
SMB	✓
Supported features on unifi.ui.com	
RAID Type	RAID 5 RAID 6 RAID 10

RAID Group	Multiple
Hot Spare Support	✓
Personal Drive & Shared Drive ⓘ	✓
SSD Cache	✓
Max. NVMe SSD Capacity Supported	4 TiB
File Encryption	✓
Backup to Remote UNAS	✓
Backup to CIFS/SMB Server	✓
Backup to Cloud Services (Google Drive, OneDrive, Dropbox, Amazon S3, Backblaze B2, Wasabi)	✓
Snapshots ⓘ	✓
Share Links ⓘ	✓
Time Machine Backup ⓘ	✓
Client App Support ⓘ	✓
User Groups ⓘ	✓

Stay in Touch

Email 



[Terms of Service](#) | [Privacy Policy](#) | [Legal](#) | [Cookies Settings](#)

© 2026 Ubiquiti, Inc. All rights reserved.